

# NHHSS-65BT4-3XKIT



Tri-sector solution that includes 3 NHHSS-65B-R2BT4-V1 antennas and mounting kit to install them on a pipe

- Suitable for attachment to 3.5-6.5 in or 89-165 mm outer diameter pipe
- Compatible with canister concealment shrouds with inner diameter > 23.5 in (597mm)
- Minimum shroud diameter is the same for all applicable pipe diameters

## General Specifications

<b>Band</b>	Multiband
<b>Performance Note</b>	Outdoor usage
<b>RF Connector Interface</b>	4.3-10 Female
<b>RF Connector Location</b>	Bottom
<b>RF Connector Quantity, high band</b>	12
<b>RF Connector Quantity, mid band</b>	12
<b>RF Connector Quantity, low band</b>	6
<b>RF Connector Quantity, total</b>	30

## Electrical Specifications

<b>Operating Frequency Band</b>	1695 – 2200 MHz   3100 – 4000 MHz   698 – 896 MHz
---------------------------------	---

## Packaging and Weights

<b>Width, packed</b>	596 mm   23.465 in
<b>Depth, packed</b>	1022 mm   40.236 in
<b>Length, packed</b>	2283 mm   89.882 in
<b>Weight, gross</b>	166 kg   365.967 lb

## \* Footnotes

<b>Performance Note</b>	Severe environmental conditions may degrade optimum performance
-------------------------	---