

FVV-65B-3XKIT



Tri-sector solution that includes 3 FVV-65B-R3-V1 antennas and mounting kit to install them on a pipe

- Suitable for attachment to 3.5-6.5 in or 89-165 mm outer diameter pipe
- Compatible with canister concealment shrouds with inner diameter > 23.5 in (597mm)
- Minimum shroud diameter is the same for all applicable pipe diameters

General Specifications

Band	Multiband
Performance Note	Outdoor usage
RF Connector Quantity, high band	12
RF Connector Quantity, low band	6
RF Connector Quantity, total	18

Dimensions

Net Weight, with mounting kit	114 kg 251.327 lb
--------------------------------------	---------------------

Electrical Specifications

Operating Frequency Band	1695 – 2690 MHz 617 – 894 MHz
---------------------------------	---------------------------------

Packaging and Weights

Width, packed	596 mm 23.465 in
Depth, packed	1022 mm 40.236 in
Length, packed	2283 mm 89.882 in
Weight, gross	149 kg 328.488 lb

* Footnotes

Performance Note	Severe environmental conditions may degrade optimum performance
-------------------------	---